

## **Main Features:**

- Input Voltage: 120~277Vdc
- Output Wattage: Constant Current (C.C.) at 60W

with Adjustable Current Setting

- Programmable Method: Wiring with Bluetooth Programmer
- High Efficiency: Up to **89%**
- Dimming Function: 0-10V with Dim to off (dto)
- Lightning Protection: Built-in [Line to line 2.5kV, line to ground 2.5kV
- Reliability Protection: SCP, OTP
- Safety Regulation: Complies with UL8750 Class 2 & Class P
- Waterproof Rating: IP20
- Five Year Warranty under Normal Usage Conditions





Model No. <sup>(*)</sup>	Output Voltage	C.C. or C.P. Programmable	Programming	Dimming Control	Dim to off (dto)	Aux	
Woder No. **	Range	Rated Output or Range	Method	Method			
LDD-www(D)vvv(P/F)ccccHH-(V/D)	(Vdc)	(mA) <sup>(i)</sup>			(V or %)	(Vdc)	
LDDS060D038P1600-U-V	10 - 54	600 - 1600	Analog/Wire	0-10V	1V or 10%	12	
(*) model name pattern:	<sup>(i)</sup> Pre-set Consta	(i) Pre-set Constant Current Value with dimming					
LDD-www(D)vvv(P/F)ccccHH-(V/D)	Auxiliaries	Voltage: 12Vaux with 100mA					
LDD means, LED Driver with C.C.	Dim to Off (dto) with 0.5W Standby Power						
(D) means, 12V Aux	Case Tamp: Tc: <b>85°C</b>						
(P/F) means, Wire/Wireless	SCP (Short Circuit Protection): when its load is being shorted, the driver will enter hiccup mode, and s				and shall		
Programming method	be self-recover when the fault condition is clean.						
(V/D) means, Analog Voltage/Digital	OTP (Over Temperature Protection): Reduce the output current to about 50mA once Ta≧75±10°C; Recover						
DALI Dimming method	only If restart the input power at Ta $\leq$ 50 $\pm$ 10°C .						

Input Spec.	Condition Description	Min.	Normal	Max.	Units
Input Voltage Range Universal Input		108	120/277	305	VAC
Input Frequency Range		47	50/60	63	Hz
Input Current	At 120 VAC/277 VAC input, full load output			0.6/0.28	А
Power Factor At 120 VAC/277 VAC input, 25°C full load			>0.95		



**SPECIFICATION** 



# LED Driver C.C. 60W Programmable Series

(in Steel Case version)

Inrush Current	At 120 VAC input, 25°C cold start / At 277 VAC input, 25°C cold start		20	А
Leakage Current	@277Vac 60Hz		0.5	mA
Surge Protection	Differential and common mode, combination wave		2.5K	

Output Spec. Condition Description		Min.	Normal	Max.	Units
Current Accuracy At 25°C, @120Vac & 277Vac, full load			±5		%
Dinale Current	At 25°C, full load, measured at 20MHz bandwidth. The result			F	0/ In n (In)
Ripple Current	differs according to different LED load characteristic.			Э	% ip-p (io)
Overshoot/Undershoot % of I out max & LED load, at 25°C, measured at 20MHz bandwidth				10	%
Turn-On Delay Measured at 120Vac/277Vac input and Full Load				0.5	S
Aux Output Voltage	utput Voltage Aux out current with 100mA up to 1.2W max		12	13	Vdc

General Spec.	Condition Description		Normal	Max.	Units
Efficiency	120Vac   277Vac measured at 25°C, full load		88 89		%
MTBF	at Tc = 25 $^\circ\!\!\mathrm{C}$ Full load and nominal input condition		≥500,000		Hours
Lifetime	at Tc < 80 $^\circ\!\!\mathrm{C}$ Full load and nominal input condition		≥50,000		Hours
Operating/Storage		20/40		FF /0F	°C
Temperature	10%KH <sup>2</sup> ~85%KH/5%KH <sup>2</sup> ~95%KH	-30/-40		22/82	
Dimension	OL is the overall length with mounting plates	152/128 x 33.0 x 28.0			mm
(OL/L x W x H)	OL is the overall length with mounting plates	6.0/5.0 x 1.30 x 1.1			inch
Weight	Net weight without package	0.66/0.3		lb/kg	

Safety & EMC Compliance	Category	Condition Description	
	UL8750	Light Emitting Diode (LED) Equipment for Use in Lighting Products, Class 2	
	Dielectric Strength (Hi-POT)	Primary to Secondary: 2500Vac /10mA max / 60 seconds (3 seconds for production)	
Cofoty Dogulations	Insulation Resistance	50M ohm min. @primary to secondary	
Salety Regulations	IEC 61000-3-3	Voltage fluctuations & flicker	
	FCC Part 15	Class A	
	IEC 61000-4-2	Electrostatic discharge (ESD): 8 kV air discharge, 4 kV contact discharge, criteria A	
EMS Standards	IEC 61000-4-4	Electrical fast transient (EFT)/ burst-EFT 2kV/5KHz	
	IEC 61000-4-5	Surge immunity test, differential and common mode, 2.5kV, combination wave	



## Dimming Curve

Parameter	Min.	Тур.	Max.
Vdim Sourcing Current	200uA	500uA	1mA
Vdim Allowed Input Voltage	-15 V		15 V
0-10V Dimming Range	0% (Vdim=1V)	Linear	100% (Vdim=9~10V)

**Dimming Wire** 



## Operating Window

Make sure that the LED driver is operated within the given window under all the operation conditions. Special attention needs to be paid at dimming as the forward voltage of the connected LED modules varies with the dimming level.





### ■ Lifetime vs. Case Temperature



### Mechanical Outline (Unit: mm)

Note: Dimensions in millimeters, where 25.4 mm = 1 inch

Tolerance: ±0.51 mm





### Figure 29, MR6YT



## ■ Wiring :(±20mm)

### Input wiring:

White & Black : 300mm  $\pm$  10mm , strip 10mm Tin Plated ,18AWG ,UL1015 .

### Output wiring:

Red & Blue : 300mm  $\pm$  10mm , strip 10mm Tin Plated ,18AWG ,UL1015 .

### **Dimming wiring:**

Purple & Gray (or Pink ) : 270mm  $\pm$  10mm , strip 10mm Tin Plated , 22AWG ,UL1569 .

#### Vaux wiring:

Black / White : 270mm  $\pm$  10mm , strip 10mm Tin Plated , 22AWG ,UL1569 .

**Safety Note:** Please make sure the output cable does not connect to dimming cable or the cables of other drivers until 20 seconds after being tested because of the remained voltage in the output capacitor.



## Revision

Date	Rev.	Description of Change				
		Item				
4/18/2020	V1a	In Draft Release				
1/8/2021			Waterpr	oof level		
	V1b		Lightning	protection		
			Programma	able method		
		Waterproof level	IP54	IP20		
		Warranty year	Three Year	Five Year		
0/45/0004	\/ <b>4</b> -	Weight	1.30/0.60	0.66/0.3		
3/15/2021	V1C		200uA-300uA-	200uA-500uA-1mA		
		Vdim Sourcing Current	450uA			
		Vdim Allowed Input Voltage	-20V~20V	-15V~15V		
			when ambient temp	Reduce the output current to about 50mA once Ta≧		
		OTP description	is over about 70 $^\circ$	75 $\pm$ 10°C; Recover only If restart the input power at		
			C, the driver output	Ta≦50±10°C .		
			current will reduce			
			to ~50mA and			
			recover the driver			
2/18/2022	V1c		restarts.			
		Тс	<b>85</b> ℃	90°C		
		Andrah M/inimen	1	Input wiring、Output wiring、Dimming wiring、		
		Add Winng	1	Vaux wiring		
		Add Lifetime vs. Case	,	Lifetime vs. Case Temperature		
		Temperature	1			
		Dimming Wire	1	Vaux		